PARTS LISTS

CAPACITORS

No.	Description	Code No.
C1	100pF mica 10%	
C2, 7	30pF air trimmer	CZ.113.700
C3, 13	0.1mF 200V paper	
C4, 5	2 gang tuning MAS1001	CZ.107.743
C4, 5	2 gang tuning MAS1001A	CZ.107.733
C6, 20	0.01mF 600V paper	
C8	450pF mica MAS1001	
C8	500pF mica MAS1001A	
C9	100pF mica	
C10, 12	24mF 350V electrolytic	
C11, 19	500pF mica	
C14	33pF mica 10%	
C15, 16	100pF ceramic	CZ.096.602
C17	0.05mF 200V paper	
C18	0.05mF 400V paper	
C21	0.02mF 600V paper	
C22	250pF mica	
C23	20pF mica 10%	

RESISTORS

No.	Description	Code No.
R1, 2	25,000 ohms 1W carbon	
R3, 12, 19	50,000 ohms ½W carbon	
R4	1 megohm ½W carbon	
R5	30,000 ohms 1W carbon	
R6	100 ohms 1W W/W	
R7	35 ohms 1W W/W	
R8	1,000 ohms 5W W/W	
R9, 10, 17	2 megohms ½W carbon	
R11	250,000 ohms ½W carbon	
R13	100,000 ohms ½W carbon	
R14	0.5 megohm switch potentiometer	CZ.032.005
R15	15,000 ohms 1W carbon	
R16	100,000 ohms 1W carbon	
R18	0.5 megohm ½W carbon 10%	
R20	50 ohms ½W carbon	
R21	25 ohms ½W carbon	

COILS

No.	Ohms.	Description	Code No.
L1	26	Aerial coil MAS1001 (red spot)	CZ.323.000
L2	2.2		
L1	28	Aerial coil MAS1001A (blue spot)	CZ.323.001
L2	2.6		
L3	3.4	Oscillator coil (red spot)	CZ.330.600
L4	1.2		
L5	12	1st I.F. Transformer	CZ.320.421
L6	12		
L7	12	2nd I.F. Transformer	CZ.320.420
L8	12		
L9	480	Speaker Transformer	CZ.345.004
L10	1		
L11	3	Speaker	CZ.161.112
L12	60	Power Transformer	CZ.344.036
L13	600		
L14	1		
L15	< 0.5		

IMPORTANT! In ordering spare parts, quote CODE NUMBER of part and MODEL NUMBER of Receiver. In claiming free replacement under GUARANTEE, return defective part PROMPTLY and quote MODEL and SERIAL NUMBER of Receiver and DATE OF PURCHASE.