

11 - 21 STURT STREET, SOUTH MELBOURNE.

21.11.38.

AUTO RADIO SERVICE BULLETIN.SUBJECT - PARTS & PRICE LIST FOR MODELS 6395 AND 12395
ASTOR AUTOMOBILE RECEIVER.

<u>CIRCUIT</u> <u>NO.</u>	<u>DESCRIPTION</u>	<u>RATING</u>	<u>TOL. SPEC.</u> <u>P/M. NO.</u>	<u>PART</u> <u>NO.</u>	<u>RETAIL</u> <u>PRICE.</u>
1.	Steel chassis base				
2.	Fuse holder.				
3.	6V. Non Synchronous vibrator			PM131	£1. 5.0.
4.	Power Transformer cover				
5.	84 tube			PM152	17.0.
6.	41 and 84 Shield				
7.	Primary Adjusting screw No.2 IF Transformer				
8.	6K7 tube			PM207	18.6.
9.	Secondary Adjusting Screw No.1 IF Transformer				
10.	No.1 IF Transformer CG		783	PT165	9.0.
11.	Primary Adjusting Screw No.1 IF Transformer.				
12.	Oscillator Transformer.		791	PT171	5.0.
13.	Oscillator trimmer		772	PC203	5.0.
14.	30uuf. Wirewound capacity		795	PC216	1.6.
15.	Bearing bracket for Control spindle.				
16.	Condenser Rotor Drive Gear Segment.				
17.	Insulating washer.				
18.	Spring Washer.				
19.	Condenser Gears and Spring Assembly.				
20.	Condenser Rotor pulley				
21.	Guide Pulley and Bearing Rivet.				
22.	R.C. Midget speaker Socket.			PM149	2.0.
23.	Battery Cable.				
24.	6/10mfd. Electrolytic Condenser		776	PC206	14.0.
25.	41 Tube			PM150	16.6.
26.	6B8 Tube			PM208	£1. 0.0.
27.	Secondary Adjusting Screw No. 2 IF Transformer.				

11 - 21 STURT STREET, SOUTH MELBOURNE.

AUTO RADIO SERVICE BULLETIN.

CIRCUIT NO.	DESCRIPTION	RATING	TOL. P/A.	SPEC. NO.	PART NO.	RETAIL PRICE.
28.	No.2 IF Transformer			784	PT166	9.0.
29.	300 ohm Filter choke			790	PT172	9.0.
30.	6A8 Tube				PM209&1.	0.0.
31.	Aerial Trimmer			772	PC203	5.0.
32.	Antenna Socket.					
33.	Antenna Transformer			782	PT164	7.0.
34.	Condenser Mount clamp					
35.	Two Gang Tuning condenser.			798	PC215&1.	1.0.
36.	Condenser Adjusting clamp.					
37.	3.5 ohm Wirewound Resistor		10%	687	PR169	1.6.
38.	6-8 Volt .15 amp Pea Lamp BC type				PM220	1.0.
39.	1 meg. Midget Volume control & switch & knob.					
40.	Dial Retaining clip (small)					
41.	Dial & Control bracket.					
42.	Glass dial Reading.					
43.	Push Buttons & Re- taining clips.					
44.	Dial Pointer					
45.	Dial Pointer drive cord.					
46.	Dial Retaining clip (Large)					
47.	Tuning Control spin- dle & knob.					
48.	30 Turn Hash choke.			617	PT116	3.0.
49.	6 pin socket.				PM145	11.
50.	Vibrator choke CG			780	PT162	2.6.
51.	.05mfd. Paper cond.	200V.20%			PC102	2.3.
52.	.5mfd. Paper cond.	200V.20%			PC121	2.6.
53.	5 pin socket				PM144	10.
54.	.004mfd. Mica cond.	2000V.10%			PC143	4.6.
55.	250,000 ohm resist.	1/4W.10%			PR108	1.6.
56.	750,000 ohm resist.	1/4W.20%			PR186	1.6.
57.	1.7 megohm resist.	1/4W.20%			PR109	1.6.
58.	.1mfd. Stedipower cond.	400V.20%			PC131	2.3.
59.	8 pin socket.				PM148	1.1.

AUTO RADIO SERVICE BULLETIN.

CIRCUIT NO.	DESCRIPTION	RATING	TOL. P/M.	SPEC. NO.	PART NO.	RETAIL PRICE.
60.	.1mfd. Stedipower Cond.	400V.	20%		PC131	2. 3.
61.	20,000 ohm resist.	1 W.	10%		PR171	1. 9.
62.	100,000 ohm resist.	1/4W.	20%		PR101	1. 6.
63.	.05mfd. Chanex Cond.	200V.	20%		PC102	2. 3.
64.	.1mfd. Stedipower Cond.	400V.	20%		PC131	2. 3.
65.	30,000 ohm resist.	1/2W.	10%		PR151	1. 6.
66.	150uuf. to 500uuf. Series Pad No.10			710	PC164	3. 6.
67.	50,000 ohm resist.	1/4W.	10%		PR105	1. 6.
68.	Series Pad Adjusting screw.					
69.	Cam Plate pulley.					
70.	Control spindle drive cord.					
71.	Hash shield.					
72.	.5mfd. Metalclad cond.	200V.	20%		PC118	4. 6.
73.	.006mfd. Chanex cond.	600V.	20%		PC224	2. 3.
74.	6 pin socket.				PM145	11.
75.	.05mfd. Stedipower Cond.		20%		PC132	2. 3.
76.	8 pin socket				PM148	1. 1.
77.	.00025mfd.Mica cond.	1000V.	10%		PC126	2. 6.
78.	500,000 ohm resist.	1/4W.	20%		PR112	1. 6.
79.	.05mfd. Chanex cond.	200V.	20%		PC102	2. 3.
80.	500,000 ohm resist.	1/4W.	20%		PR112	1. 6.
81.	.0001mfd.Mica cond.	1000V.	10%		PC110	2. 6.
82.	.00025mfd.Mica cond.	1000V.	10%		PC126	2. 6.
83.	50 ohm Wire wound resistor	2W.	10%	702	PR174	1. 9.
84.	1 megohm resist.	1/4W.	20%		PR110	1. 6.
85.	50,000 ohm resist.	1/4W.	20%		PR134	1. 6.
86.	.01mfd. Chanex cond.	400V.	20%		PC225	2. 3.
87.	.00025mfd.Mica cond.	1000V.	10%		PC126	2. 6.
88.	250,000 ohm resist.	1/4W.	20%		PR133	1. 6.
89.	.25mfd.Paper cond.	200V.	20%		PC146	2. 6.
90.	500,000 ohm resist.	1/4W.	20%		PR112	1. 6.
91.	Transformer can earthing strip.					
92.	8 pin socket				PM148	1. 1.
93.	Antenna socket & choke shield can.					

11 - 21 STURT STREET, SOUTH MELBOURNE.

21.11.38.

AUTO RADIO SERVICE BULLETIN.

CIRCUIT NO.	DESCRIPTION	RATING	TOL. SPEC. P/M. NO.	PART NO.	RETAIL PRICE.
94.	.05mfd.Chanex cond.	200V. 20%		PC102	2.3.
95.	Cam plate Bearing screws.				
96.	Cam plate.				
97.	Plunger Housing				
98.	Push Button Return spring				
99.	Cam clamp screw.				
100.	Button plunger.				
101.	Cam Setting Clamp.				
102.	Setting cam.				
103.	20turn Spiral hash choke		677	PT137	1.6.
104.	.1mfd.Chanex cond. 200V.	20%		PC218	2.3.
105.	400 ohm C.T.Wire- wound resistor	10%	799	PR189	2.6.
106.	21 ohm Wirewound resistor	-10%	800	PR190	2.0.
107.	3,000 ohm resist. 1/4W.	20%		PR185	1.6.
108.	.1mfd. Stedipower 400V. cond.	20%		PC131	2.3.
109.	20 ohm Wirewound resistor	5%	801	PR191	2.0.
110.	6V. Auto Power Transformer		781	PT163£1.	0.0.
111.	Antenna Spark choke		691	PT138	1.6.
112.	12V. Auto Power Transformer.		794	PT174£1.	0.0.
113.	50 ohm Wire wound Resistor	2W. 10%	702	PR174	1.9.
114.	.001mfd.Mica cond.1000V.	10%		PC108	2.6.
115.	12V. Non Synchron- ous Vibrator			PM132£1.	5.0.
116.	15 amp Fuse			PM219	3.
117.	Speaker Input Transformer.)	793	PM206	-
118.	6" Underdash speaker 4 ohm Field)			
119.	.001mfd.Mica cond.1000V.	10%		PC108	2.6.

AUTO RADIO SERVICE PULETIN.

CIRCUIT NO.	DESCRIPTION	RATING	TCL. SPEC. P/M.	PART NO.	RETAIL NO.	PRICE.
----------------	-------------	--------	-----------------	----------	------------	--------

ACCESSORIES.

Distributor Suppressor				A1006A		3.0.
12 Volt						
Distributor Suppressor				A1008		3.0.
6 volt						
Condenser Metal Clad 200V. 20%				A1009		4.6.
.5mfd.						
Rear Mounting strap				3901		
Drilling Template				3902		
No.10 x 3/4" Binder				3843		
Head Parker Kalon						
Screws & washers.						
5/16"Whit.x1-1/2"				3903		
Coach bolts & nuts.						
1-1/4"dia.x11/32"x16gge.				3904		
Lead Coated Steel large						
Mounting washers.						

SERVICE EQUIPMENT.

Dummy Aerial & Lead	PM157	10.6.
Aligning tool	PM158	4.0.

THIS BULLETIN CANCELS PARTS AND PRICE LIST, BULLETIN P6
PAGES 1, 2, 3, 4 AND 5, ISSUED ON 15.10.38.

AUTO RADIO SERVICE BULLETIN

SUBJECT - PARTS & PRICE LIST FOR MODELS 6395 and 12395

ASTOR AUTOMOBILE RECEIVER. CHASSIS TYPE CG & HC

CIRCUIT NO.	DESCRIPTION	RATING	TOL. P/M.	SPEC. NO.	PART NO.	RETAIL PRICE.
1.	Steel Chassis base					
2.	Fuse holder.					
3.	6V Non Synchronous vibrator				PM131	£1. 5. 0.
4.	Power Transformer cover					
5.	84 tube				PM152	17. 0.
6.	41 and 84 Shield					
7.	Primary Adjusting screw No.2 IF Transformer					
8.	6K7 tube				PM207	18. 6.
9.	Secondary Adjusting Screw No.1 IF Transformer					
10.	No.1 If Transformer CG			783	PT165	9. 0.
11.	Primary Adjusting Screw No.1 IF Transformer.					
12.	Oscillator Transformer.			791	PT171	5. 0.
13.	Oscillator trimmer			772	PC203	5. 0.
14.	30uuf. Wirewound Capacity			795	PC216	1. 6.
15.	Rearring bracket for Control spindle.					
16.	Condenser Rotor Drive Gear Segment.					
17.	Insulating washer.					
18.	Spring Washer.					
19.	Condenser Gears and Spring Assembly.					
20.	Condenser Rotor pulley					
21.	Guide Pulley and Bearing Rivet.					
22.	R.C. Midget speaker Socket.				PM149	2. 0.
23.	Battery Cable					
24.	6/10 mfd. Electrolytic Condenser			776	PC206	14. 0.
25.	41 Tube				PM150	16. 6.

AUTO RADIO SERVICE BULLETIN

<u>CIRCUIT NO.</u>	<u>DESCRIPTION</u>	<u>RATING</u>	<u>TOL. P/M.</u>	<u>SPEC. NO.</u>	<u>PART NO.</u>	<u>RETAIL PRICE.</u>
26.	6B8 Tube				PM208	£1. 0. 0.
27.	Secondary Adjusting Screw No.2 IF Transformer					
28.	No. 2 IF Transformer			784	PT166	9. 0.
29.	300 ohm Filter choke			790	PT172	9. 0.
30.	6A8 Tube				PM209	£1. 0. 0.
31.	Aerial Trimmer			772	PC203	5. 0.
32.	Antenna Transformer			782	PT164	7. 0.
33.	Antenna Socket					
34.	Condenser Mount Clamp					
35.	Two Gang Tuning Condenser.			798	PC215	£1. 0. 0.
36.	Condenser Adjusting clamp.					
37.	3.5 ohm Wirewound Resistor		10%	687	PR169	1. 6.
38.	6-8 Volt .15 amp Pea Lamp B& Type				PM220	1. 0.
39.	1 meg. Midget Volume control & switch & Knob.					
40.	Dial Retaining Clip (small)					
41.	Dial & Control bracket.					
42.	Glass dial Reading.					
43.	Push Buttons & Re- taining clips.					
44.	Dial Pointer.					
45.	Dial Pointer drive cord.					
46.	Dial Retaining clip (large)					
47.	Tuning Control Spindle and knob.					
48.	30 Turn Hash Choke.			617	PT116	3.0.
49.	6 pin socket.				PM145	11d.M.
50.	Vibrator choke CG			780	PT162	2.6
51.	.05 mfd. Paper Cond. 200V	20%			PC102	2.5
52.	.5 mfd Paper Cond	200V	20%		PC121	2.6
53.	5 pin socket				PM144	10.
54.	.004 mfd. Mica Cond 2000V	10%			PC143	4.6

AUTO RADIO SERVICE BULLETIN.

CIRCUIT NO.	DESCRIPTION	RATING	TOL. P/M.	SPEC. NO.	PART. NO.	RETAIL PRICE.
55.	250,000 ohm resist.	1/4W.	10%		PR108	1.6
56.	750,000 ohm resist.	1/4W.	20%		PR186	1.6
57.	1.7 megohm resist.	1/4W.	20%		PR109	1.6
58.	.1 mfd Stedipower Cond.	400V	20%		PC131	2.3
59.	8 Pin socket				PM148	1.1
60.	.1 mfd. Stedipower Cond.	400V	20%		PC131	2.3
61.	20,000 ohm Resis.	1W.	10%		PR171	1.9
62.	100,000 ohm resis.	1/4W.	20%		PR101	1.6
63.	.05 mfd. Chanex Cond.	200V	20%		PC102	2.3
64.	.1 mfd. Stedipower Cond.	400V.	20%		PC131	2.3
65.	30,000 ohm resis.	1/2W.	10%		PR151	1.6
66.	1500uuf. to 500uuf			710	PC164	3.6
EX.	Series Pad No.10					
67.	50,000 ohm resis.	1/4W.	10%		PR105	1.6
68.	Series Pad Adjusting screw.					
69.	Cam Plate Pulley.					
70.	Control spindle drive cord.					
71.	Hash shield.					
72.	.5mfd Metalclad cond.	200V.	20%		PC118	4.6
73.	.006 mfd Chanex cond	600V	20%		PC224	2.3
74.	6 pin socket				PM145	1.1
75.	.05 mfd. Stedipower cond.		20%		PC132	2.3.
76.	8 pin socket				PM148	1.1
77.	.00025 mfd. Mica cond.	1000V	10%		PC126	2.6
78.	500,000 ohm resist.	1/4W.	20%		PR112	1.6
79.	.05 mf.d Chanex cond.	200V	20%		PC102	2.3
80.	500,000 ohm resist.	1/4W.	20%		PR112	1.6
81.	.0001 mfd. Mica cond.	1000V	10%		PC110	2.6
82.	.00025 mfd. Mica cond	1000V	10%		PC126	2.6
83.	50 ohm Wire wound resistor	2 watt	10%	702	PR174	1.9
84.	1 megohm resist.	1/4W.	20%		PR110	1.6
85.	50,000 ohm resist.	1/4W.	20%		PR134	1.6
86.	.01 mfd. Chanex cond.	400V.	20%		PC225	2.3
87.	.00025 mfd. Mica Cond.	1000V.	10%		PC126	2.6

AUTO RADIO SERVICE BULLETIN

CIRCUIT NO.	DESCRIPTION	RATING	TOL. P/M.	SPEC. NO.	PART. NO.	RETAIL PRICE.
88.	250,000 ohm resist 1/4W.20%				PR133	1.6
89.	.25 mfd. Paper Cond 200V.20%				PC146	2.6
90.	500,000 ohm resist. 1/4W.20%				PR112	1.6
91.	Transformer can earthing strip.					
92.	8 pin socket				PM148	1.1
93.	Antenna Socket & choke shield can					
94.	.05 mfd. Chanex 200V. 20%				PC102	2.3
95.	Cam plate Bearing screws					
96.	Cam Plate.					
97.	Plunger Housing					
98.	Push Button Return spring					
99.	Cam clamp screw.					
100.	Button plunger.					
101.	Cam Setting Clamp.					
102.	Setting cam.					
103.	20 turn Spiral hash choke			677	PT137	1.6
104.	.1 mfd. Chanex cond. 200V 20%				PC218	2.3
105.	400 ohm C.T. Wire- wound resistor		10%	799	PR189	2.6
106.	21 ohm Wirewound resistor		-10%	800	PR190	2.0
107.	3,000 ohm resist.1/4W. 20%				PR185	1.6
108.	.1 mfd. Stedipower 400V. 20% cond.				PC131	2.3
109.	20 ohm Wirewound resistor		5%	801	PR191	2.0.
110.	6V. Auto Power Transformer			781	PT163	£1.0.0.
111.	Antenna Spark Choke			691	PT138	1.6
112.	12V. Auto Power Transformer.			794	PT174	£1.0.0.
113.	50 ohm Wire wound 2W. 10% Resistor			702	PR174	1.9
114.	.001 mfd. Mica Cond.100V10%				PC108	2.6
115.	12V. Non Synchronous Vibrator				PM132	£1.5.0
116.	15 amp Fuse				PM219	3.
117.	Speaker Input Trans.)			793	PM206	-
118.	6" Underdash speaker)					
119.	4 ohm Field) .001 mfd. Mica Cond 1000V. 10%				PC108	2.6

AUTO RADIO SERVICE BULLETIN

<u>CIRCUIT</u> <u>NO.</u>	<u>DESCRIPTION</u>	<u>RATING</u>	<u>TOL.</u> <u>P/M.</u>	<u>SPEC.</u> <u>NO.</u>	<u>PART</u> <u>NO.</u>	<u>RETAIL</u> <u>PRICE.</u>
<u>ACCESSORIES.</u>						
	Distributor Suppressor 12 Volt				A1006A	3.0.
	Distributor Suppressor 6 Volt				A1008	3.0
	Condenser Metal Clad 200 V. 20% .5 mfd.				A1009	4.6.
	Rear Mounting strap				3901	
	Drilling Template				3902	
	No.10 x 3/4" Binder				3843	
	Head Parker Kalon					
	Screws and washers.					
	5/16" Whit x 1-1/2"				3903	
	Coach bolts & Nuts.					
	1-1/4" dia. x 11/32" x 16 gge.				3904	
	Lead Coated Steel large Mounting washers.					

SERVICE EQUIPMENT.

Dummy Aerial & Lead	PM157	10.6
Aligning tool	PM158	4.0

THIS BULLETIN CANCELS PARTS AND PRICE LIST, BULLETIN P6
PAGES 1, 2, 3, 4 AND 5, ISSUED ON 21.11.38.
