AUTO RADIO SERVICE BULLETIN.

SUBJECT - PARTS & PRICE LIST FOR MODELS 6396 and 12396 ASTOR AUTOMOBILE RECEIVER.

CIRCUIT NO.	DESCRIPTION	RATING	TOL. P/M	SPEC. NO.	PART NO.	RETAIL PRICE
1.	Steel chassis base					
2.	RF gang trimmer					
3.	3 gang tuning condenser			845	PC232	30/-
4.	6A8 tube				PM209	20/-
5.	No.1 IF transformer			682	PT132	15/-
6.	Primary adjusting screw No.1 IF					
7.	Secondary adjusting screw No.1 IF					
8.	6B8 tube				PM208	20/-
9.	6K7 tube				PM207	18/6
10.	No.2 IF transformer (Includes 105, 106, 107, 108)			826	PT186	
11.	Primary adjusting screw No.2 IF					
12.	Secondary adjusting screw No.2 IF					
13.	6F8G tube				PM244	17/6
14.	6 volt non-synchronous					25/-
15.	vibrator 150 cycle			819	PM237	
15.	Vibrator earthing clip					
16.	Transformer shield box					
17.	6X5 tube				PM256	19/6
18.	6N7 tube				PM243	20/-
19.	Tone control socket					
20.	Battery cable					
21.	10/10 mfd Electrolytic condenser	450VP	20%	818	PC228	9/-
22.	Class B PP Coupling transformer			814	PT179	7/-
23.	Choke sleeve					
24.	Oscillator trimmer (Air dielectric			772	PC203	5/-
25.	Midget RC speaker socket			698	PM149	2/-
26.	Speaker socket earth spring					
27.	Synchro padder adjusting nut					
28.	Synchro padder adjusting screw					
29.	Antenna synchro tuning padder			693	PC181	5/-

AUTO RADIO SERVICE BULLETIN.

CIRCUIT NO.	DESCRIPTION	RATING	TOL. P/M	SPEC. NO.	PART NO.	RETAIL PRICE
30.	Worm lock nut					
31.	Worm adjusting screw					
32.	Fuse holder					
33.	Aerial contact					
34.	Aerial earthing clip					
35.	Worm drive					
36.	Worm bracket					
37.	Rotor shaft drive gears					
381	Aerial gang trimmer					
39.	Tapped filter choke			815	PT180	6/-d.
40.	Antenna spark choke			691	PT138	1/6
41.	.25 mfd Chanex condenser	200V	20%		PC146	2/6
42.	.1 mfd Stedipower "	400V	20%		PC131	2/3
43.	1 megohm IRC Resistor	1/4watt	20%		PR110	1/6
44.	Take-up Spring (Vol. Cont. Shaft)					
45.	.004 mfd Simplex cond.	1000V	10%		PC119	2/3
46.	8 pin socket				PM148	1/1
47.	40,000 ohm IRC Resistor	1/4watt	20%		PR204	1/6
48.	1 megohm Midget volume control (tapped)				PR205	6/-
49.	.00025 mfd Simplex cond.	1000V	10%		PC126	2/6
50.	.006 mfd Chanex cond.	600V	20%		PC238	2/3
51.	Universal wound RF choke			664	PT109	4/6
52.	.008 mfd Chanex cond.	600V	20%		PC113	2/3
53.	8 pin socket				PM148	1/1
54.	.02 mfd Chanex cond.	400V	20%		PC111	2/3
55.	Vibrator partition					
56.	12V Non-synchronous vibrator 150 cycle				PM238	25/-
57.	8 pin socket				PM148	1/1
58.	EB hash plates				PC239	2/3
59.	.004 mfd. TCC Condenser	2000V	10%		PC143	4/6
60.	500,000 ohm IRC Resistor	1/4watt	20%		PR112	1/6
61.	30 turn hash choke			617	PT116	3/-
62.	1 mfd Chanex condenser	200V	20%		PC218	2/3
63.	.25 mfd Chanex cond.	200V	20%		PC146	2/6
64.	.05 mfd Chanex cond.	200V	20%		PC102	2/3
65.	200,000 ohm IRC Resistor	1/4watt	20%		PR135	1/6
66.	.02 mfd Stedipower Cond.	400V	20%		PC155	2/3
67.	Small hash choke			677	PT137	1/6

AUTO RADIO SERVICE BULLETIN.
&

CIRCUIT NO.	DESCRIPTION	RATING	TOL. P/M	SPEC. NO.	PART NO.	RETAIL PRICE
68.	Mount bracket for hash cover					
69.	6 pin socket				PM145	11d.
70.	200 ohm W.W. IRC Resistor	1watt	10%		PR206	1/9
71.	.1 mfd Chanex condenser	200V	20%		PC218	2/3
72.	Chassis mounting holes					
73.	20 ohm W.W. Resistor	1/4watt	5%	801	PR191	2/-
74.	100,000 ohm IRC resistor	1/4watt	10%		PR130	1/6
75.	Filament choke			780	PT162	2/6
76.	.05 mfd Chanex Cond.	200V	20%		PC102	2/3
77.	Volume control spindle drive clutch					
78.	.00005 mfd Simplex Condenser	1000V	10%		PC141	2/6
79.	8 pin socket				PM148	1/1
80.	1 megohm IRC Resistor	1/4watt	20%		PR110	1/6
81.	1 megohm IRC Resistor	1/4 watt	20%		PR110	1/6
82.	1 megohm IRC Resistor	1/4watt	20%		PR110	1/6
83.	.1mfd. Stedipower cond.	400V	20%		PC131	2/3
84.	30,000 ohm IRC Resistor	1watt	10%		PR156	1/9
85.	EB oscillator transformer			824	PT185	8/-
86.	Series Pad 1066mmfd Simplex condenser		1%	837	PC233	3/-
87.	.00025 mfd Simplex cond.	1000V	10%		PC126	2/6
88.	30,000 ohm IRC Resistor	1/2watt	10%		PR151	1/6
89.	50,000 ohm IRC Resistor	1/4watt	10%		PR105	1/6
90.	20,000 ohm IRC resistor	1/4watt	10%		PR106	1/6
91.	8 pin socket				PM148	1/1
92.	8 pin socket				PM148	1/1
93.	.02 mfd Chanex cond.	400V	20%		PC111	2/3
94.	.05 mfd " "	200V	20%		PC102	2/3
95.	RF transformer (Includes 104)			679	PT130	10/-
96.	100,000 ohm IRC resistor	1/4watt	20%		HR101	1/6
97.	50 ohm W.W. Resistor	2watt	10%	702	PR174	1/9
98.	Antenna transformer (Includes 103)			678	PT128	15/-
99.	.05 mfd Chanex cond.	200V	20%		PC102	2/3
100.	Volume control Bush					
101.	" " Shaft					
102.	Aerial filter can					
103.	.0001 mfd Simplex cond.	1000V	P5% -0%	(In 98)	PC180	3/6

AUTO RADIO SERVICE BULLETIN

CIRCUIT NO.	DESCRIPTION	RATING	TOL. P/M	SPEC. NO.	PART NO.	RETAIL PRICE
104.	.0001 mfd Simplex cond.	1000V	P5% -0%	(In 95)	PC180	3/6
105.	.00025 mfd " "	1000V	10%	(In 10)	PC126	2/6
106.	.00025 mfd " "	1000V	10%	(In 10)	PC126	2/6
107.	50,000 ohm IRC Res.	1/4watt	20%	(In 10)	PR134	1/6
108.	500,000 ohm IRC Res.	1/4watt	20%	(In 10)	PR112	1/6
109.	400 ohm W.W. IRC Res.	1watt	10%		PR148	1/9
110.	21 ohm W.W. Resistor	1/2watt	-10%	800	PR190	2/-
111.	250,000 ohm Tone Control				PR207	6/-
112.	Speaker input trans.					
113.	EB Power Trans. 6 volt			816	PT181	20/-
114.	15 ampere fuse				PM219	3d.
115.	7 ohm EB Pea lamp resistor			840	PR203	1/9
116.	6-8 volt .15 amp pea lamp				PM220	1/-
117.	Battery switch				PM257	6/-
118.	6 mmfd W.W. Capacity			846	PC240	1/6
119.	20 mmfd W.W. Capacity			639	PC166	1/6
120.	12V AE Power Trans.			817	PT182	20/-
121.	50 ohm W.W. Pea lamp resistor				PR208	1/9

SERVICE EQUIPMENT:

Dummy aerial and leadin	PM157	10/6
1/8" flat spanner	PM254	1/-
Aligning tool	PM158	4/-
Dummy antenna adaptor	PM255	4/-

----------oOo--------