

SPECIFICATION

MODEL : 8TP-90

Receiving frequency540~1,600 KC
 IF frequency455 KC
 Power sourceLaminated 9 V (006P) battery
 Power output150 mw
 Speaker2 1/2" PM. Voice coil 8 ohms.
 AntennaFerrite core antenna (EXTERNAL antenna jack attached)


Transistors :

- 2SA521 Mixer
- 2SA521 Oscillator
- 2SA491 I. F. Amplifier
- 2SA531 I. F. Amplifier
- 1N601 Det. AGC.
- 1N601 Limitter (Germanium diode)
- 2SB541 A. F. Amplifier
- 2SB541 Driver
- 2SB562 Output

Dimensions2 5/8" x 4 3/8" x 1 1/4"
 Weight11 ozs (with battery)
 Accessories1 Magnetic earphone, 1 leather carrying case and 1 antenna lead

Batteries sold everywhere :

- 006PToshiba
- 216Eveready
- 1604Ray-O-Vac
- VS036RCA
- 2U6Burgess



CIRCUIT DIAGRAM

