



RADIO CORPORATION PTY. LTD.

DIVISION OF ELECTRONIC INDUSTRIES LTD.

126-130 GRANT STREET, SOUTH MELBOURNE, S.C.A.

TECHNICAL BULLETIN

BULLETIN G-1

File: Service,
General (G)

Date: 15/2/46.

Page 1.

SUBJECT—Service—Type M1 Cabinet Replacement.

Moulded bakelite cabinets for Models AFJQ, DNS and DQQ which require replacement are to be replaced with new cabinets the part numbers of which are as follows:-

AFJQ	Cabinet	Part	Number	49/81-2
DNS	"	"	"	24/216-3
DQQ	"	"	"	24/216-1

Four speed nuts (part number 227/250) are required with each of these cabinets.

Minor differences to the inside construction exist between the old cabinets and the new replacement types which necessitates cutting the silk card as follows:-

1. Remove silk card from old cabinet and place inside new cabinet marking on the card positions of raised bakelite studs.
2. Pull the silk back and cut sections from card at these markings so that silk card fits snugly over bakelite studs. Replace silk into position.
3. Leave card fitted in position and press a speed nut on to each of the bakelite studs.
4. Slide chassis into cabinet and finish off fitting knobs, etc.