ELECTRONIC INDUSTRIES LTD.
CAR RADIO DIVISION
126-130 GRANT STREET, SOUTH MELBOURNE, S.C.4.
SERVICE BULLETIN

BULLETIN RL/RM-5
File: Receivers
Auto
Date: 4.7.57
Page: 1

MODEL "RM" 12 VOLT RECEIVERS WITH 12 VOLT DIAL AND INDICATOR LAMPS HAVING A SERIES RESISTOR OR RESISTORS CHANGED TO 16 VOLT LAMPS WITH NO SERIES RESISTOR

The 12 volt dial and indicator lamp or lamps part No. M370, are to be changed to 16 volt lamp or lamps part No. M440, Lugon type 163-11MM min. bay. base.

When the 16 volt lamps are used the lamp series resistor, either 4.7 ohm ½W. part No. PR858 or a 4.7 ohm 1W. part No. PR859, depending on whether one or two lamps are used, are to be deleted.

The 16 volt lamps are to be connected directly across the 12 volt circuit (no series resistor required)

6" DIA PERMAG SPEAKER TYPE "6L" CHANGED TO 6" DIA PERMAG TYPE "6M"

The production of 6" dia. permag. speaker part No. K176, Rola Co. type 6L, cone No. F79 (85-95 CPS) is being discontinued. Speaker K176 will be replaced by a 6" dia. permag. speaker part No. K213 Rola Co. type 6M, cone No. F80 (85-95 CPS).

K213 will be used as a replacement for K176.