



NOTE: ALL POSITIONS MARKED 'SWBC' INDICATE SECTIONS OF A GANG WAVE CHANGE SWITCH.

# STC MODEL 77.

- C1 = 3 Gang Variable Capacitor
- C2 = Trimmer
- C3 = Padder
- C4 = 8 m.f.
- C5 = 8 m.f.
- C6 = 8 m.f.
- C7 = .006 m.f. condenser
- C8 = .1 m.f. paper "
- C9 = 25 m.f. "
- C10 = .0001 mica "
- C11 = .01 m.f. "
- C12 = .02 m.f. "
- C13 = .0085 m.f. mica condenser
- C14 = .00035 m.f. "
- C15 = .5 m.f. paper "
- R1 = .25 meg ohm resistor
- R2 = 30,000 ohm "
- R3 = 16,000 ohm volt divider
- R4 = 2 megohm resistor
- R5 = .5 megohm "
- R6 = 50,000 ohm "
- R7 = 20,000 ohm "
- R8 = 20 ohm C.T.
- R9 = 400 ohm resistor
- R10 = 5000 ohm resistor
- R11 = 1200 ohm "
- R12 = 5000 ohm "
- R13 = 1000 ohm "
- R14 = 3700 ohm "
- R15 = 1 ohm "