

682 - 4541



MODEL DATA SHEET

for

"HIS MASTER'S VOICE"

MODEL 32-4K



This model is a 5-valve A.C. mains-operated dual-wave console radiogram, incorporating a three-speed record changer.

POWER SUPPLY:

200 to 250 volts at 50 c.p.s. (40 c.p.s. operation is obtainable by fitting the correct motor unit and pulley to the record changer).

DIMENSIONS:

Width 36in.
Height 31in.
Depth 17 $\frac{3}{4}$ in.

WEIGHT:

Gross 106 lbs.
Nett 90 lbs.

RECEIVER CHASSIS:

Type 32 chassis is fitted to this model. For servicing information, refer to Chassis Type 32 Service Manual, Part No. 682-2522.

RECORD CHANGER:

Collaro Type RC54. For servicing information, refer to Collaro Service Sheet for this mechanism.

SPEAKERS:

One permagnetic 6in. Voice coil impedance, 2.7 ohms at 400 c.p.s.

One permagnetic 5in. x 7in. Voice coil impedance, 4 ohms at 400 c.p.s.

SPARE PARTS (Other than those shown in Chassis Manual):

Cabinet (without trim)—Maple	192-0861
Mechanism — Record Changer (less equaliser and leads)	558-0471
Cartridge	211-0131
Stylus—microgroove	HM6
Stylus—standard	HS8
Panel Trim—Grey	641-0521
Panel Trim—Burgundy	641-0531
Panel Trim—Primrose	641-0541
Screw—Chassis Fixing	814-0361
Speaker—5in. x 7in.	831-0225
Speaker—6in.	831-0391
Capacitor—0.001 mF \pm 10%	273-0151
Capacitor—200 mmF \pm 10%	273-0071
Resistors (2)—470K ohm \pm 10% $\frac{1}{2}$ watt	740-0182

EQUALISER: