


6822721



MODEL DATA SHEET
for
"HIS MASTER'S VOICE"
MODEL 33-51



This model is a five-valve A.C. mains-operated, dual-wave mantel receiver.

POWER SUPPLY:

200 to 250 volts at 40 to 50 c.p.s.

DIMENSIONS:

Width 12 inches
Height 9 inches
Depth 6½ inches

WEIGHT:

Gross 12 lb.
Nett 9½ lb.

RECEIVER CHASSIS:

Refer to Chassis Type 33 Service Manual.
Part No. 6822771.

SPEAKER:

Permagnetic 5 x 7 inches. Voice Coil Impedance,
4 ohms at 400 c.p.s.

SPARE PARTS

(other than those shown in Chassis Manual) :

Cabinet Front — Burgundy with Ivory Grille	1900282
Cabinet Back—Burgundy	1900201
Cabinet Front—Ivory with Ivory Grille ..	1900292
Cabinet Back—Ivory	1900071
Cabinet Front—Green with Ivory Grille ..	1900302
Cabinet Back—Green	1900221
Cabinet Front—Grey with Ivory Grille	1900381
Cabinet Back—Grey	1900391
Knob—Control	5170261
(Initial manufacture of this Model used 5170121 Ivory Knob).	
Screw—Cabinet back fixing 4BAx1½in.	8140111
Screw—Cabinet back fixing 4BAx¾in.	8140201
Speaker, 5-7 Ellipsoidal	8310056