

682-4941



## MODEL DATA SHEET

for

# "HIS MASTER'S VOICE"

## MODEL 35 - 33



This model is a 5-valve, A.C. dual-wave 3-speed table model auto-radiogram with attachable legs.

### POWER SUPPLY:

200 - 250 volts at 50 c.p.s.

### CONSUMPTION:

50 watts.

### DIMENSIONS:

	<i>Packed</i>	<i>Unpacked</i>
Width .....	23in.	21 $\frac{1}{4}$ in.
Height .....	12in.	26 $\frac{1}{4}$ in.
Depth .....	19in.	17 $\frac{1}{4}$ in.

### WEIGHT:

Gross .....	41 lbs.
Nett .....	36 lbs.

### RECEIVER CHASSIS:

For servicing information, refer to Service Manual,  
Part No. 682-4321, for Chassis Type 35.

### RECORD CHANGER:

Collaro type 54. For servicing information, refer  
Collaro service sheet—Part No. 682-3311.

### SPEAKER:

7in. x 5in. permagnetic, 4 ohms impedance at 400  
c.p.s.

### SPARE PARTS (Other than those shown in Chassis Manual):

Cabinet, Walnut, with 4 legs .....	192-0931
Cabinet, Rosewood, with 4 legs .....	192-0941
Cabinet, Maple, with 4 legs .....	192-0951
Speaker .....	831-0225
Record Changer type 54 (less cartridge) .....	558-0611
Cartridge, pick-up (complete with styli) .....	211-0191
Cartridge, pick-up (less styli) .....	211-0201
Stylus, standard (HS8) .....	611-0281
Stylus, microgroove (HM6) .....	611-0291
Capacitor C24, 250 pF. $\pm 10\%$ .....	273-0311
Capacitor C25, 0.002 mF. $\pm 10\%$ .....	273-0171
Resistor R16, R17, 270,000 ohms $\pm 10\%$ .....	740-0171

### EQUALISER:

