

**Private and Confidential**

**For Trade Use Only**

**682-4111**




## **MODEL DATA SHEET**

**for**

# **"HIS MASTER'S VOICE"**

## **MODEL 63 - 53**



This model is a five-valve A.C. mains-operated clock-controlled, medium-wave mantel receiver.

**POWER SUPPLY:**

200 to 250 volts at 50 c.p.s.

**DIMENSIONS:**

Width ..... 13in.  
Height ..... 7 $\frac{1}{4}$ in.  
Depth ..... 6 $\frac{1}{2}$ in.

**WEIGHT:**

Gross ..... 15lb.  
Nett ..... 10 $\frac{3}{4}$ lb.

**RECEIVER CHASSIS:**

Refer to Chassis Type 63 Service Manual, Part  
No. 682-4001.

**SPEAKER:**

Permagnetic 5 x 7 inches. Voice Coil Impedance,  
4 ohms at 400 c.p.s.

**SPARE PARTS** (Other than those shown in Chassis  
Manual):

Cabinet Front—Grey with Silver Grille	190-0541
Cabinet Back—Grey	190-0482
Cabinet Front — Burgundy with Silver Grille	190-0541
Cabinet Back—Burgundy	190-0462
Cabinet Front — Black with Silver Grille	190-0761
Cabinet Back—Black	190-0612
Cabinet Front — Biscuit with Ivory Grille	190-0861
Cabinet Back—Biscuit	190-0931
Knob Control: Tuning	517-0431
Tone	517-0421
Volume	517-0411
Clock	517-0581
Screw—Cabinet Back fixing and Chassis fixing—4BA x 7/16in.	814-0231