


AUSTRAL PRESS BUTTON CAR RADIO "SAPPHIRE EIGHT"

MODEL AT8 AND MODEL AT68

ALIGNMENT:

IF'S PEAK AT 455 Kcs USING OUTER SETTING OF IF TRANSFORMER CORES



TUNE TO H.F. LIMIT (TUNER CORES OUT)  
SET OSC. TRIMMER TO 1620 Kcs

TUNE TO 900 Kcs PEAK  
B/P TRIMMER }  
R/F TRIMMER } FOR  
AER. TRIMMER } MAX.

NOTE: READJUSTMENT OF TUNER CORES SHOULD NOT BE ATTEMPTED

NOTE:

SETS MANUFACTURED AFTER 1-2-66

R1 = 2.2 K ADDED

R3 NOW 120 Ω

R9 NOW 2.7 K

R21 NOW 560 Ω

C12 NOW 620 PF

CX USE 3.3 PF NEUT. COND. WITH 1936 IF

12V BRIDGE RED + BLACK  
(6V BRIDGE RED+GREEN+GR.)  
A ADD 1Ω ACROSS R9

CAR RADIO & TV Co. Pty. Ltd.

239 GLEBE RD. GLEBE