

100W OUTPUT CONNECTIONS		
No OF SPEAKERS	OUTPUT TERMINATION	JOIN FOLLOWING
4 – 6	100Ω , 100V	3 – 4, 6 – 7, 9 - 10
7 – 9	75Ω	3 – 5, 6 – 7, 8 – 10
10 – 13	55Ω	2 – 4, 6 – 7, 9 – 11
14 – 18	40Ω	3 – 4, 5 – 8, 9 – 10
19 – 29	25Ω	1 – 4, 3 – 10, 9 – 12, 6 – 7
30 – 49	15Ω	1 – 4, 2 – 7, 9 – 12, 6 – 11
50 – 100	10Ω	1 – 4, 3 – 8, 9 – 12, 5 – 10
OVER 100	6Ω	1 – 4 – 7 – 10, 3 – 6 – 9 – 12

TAP No	COLOUR
1	Black
2	Brown
3	Mauve
4	Green
5	Orange
6	Grey
7	Red
8	Blue
9	Yellow
10	Orange
11	Black
12	White

Output is 1 and 12