COMPONENT PARTS LIST

RESISTORS

All Resistors ± 10% Carbon unless otherwise stated

Code No.	Description	Part No.	Code No.	Description	Part No.
R1	3.3K ohms ½ watt	601290	R14	1.5K ohms Volume Control w/s	620014
R2	27K ohms ½ watt	601520	R15	47K ohms ½ watt	601610
R3	470 ohms ½ watt	601180	R16	10K ohms ½ watt	601400
R4	2.7K ohms ½ watt	601260	R17	1K ohms ½ watt	601210
R5	68K ohms ½ watt	601632	R18	3.3K ohms ½ watt	601290
R6	47K ohms ½ watt	601610	R19	2.2K ohms ½ watt	601240
R7	2.2K ohms ½ watt	601240	R20	47K ohms ½ watt	601610
R8	100 ohms ½ watt	601070	R21	4.7K ohms ½ watt	601340
R9	820 ohms ½ watt	601202	R22	220 ohms ½ watt	601091
R10	100 ohms ½ watt	601070	R23	100 ohms ½ watt	601070
R11	27K ohms ½ watt	601520	R24	6.8K ohms ½ watt	601362
R12	4.7K ohms ½ watt	601340	R25	1K ohms ½ watt	601210
R13	470 ohms ½ watt	601180	R26	10 ohms ½ watt	601001

CAPACITORS

Code No.	Description	Part No.	Code No.	Description	Part No.
C1	8 — 163 pf Tuning Aerial	231171	C15	0.01 uf 200 vw Hunts W99	228609
C2	1 — 9 pf Trimmer Aerial		C16	330 pf ± 5% 600 vw Styroseal	223712
C3	8 — 78pf Tuning Osc.		C17	0.04 uf 200 vw Hunts W99	228750
C4	1 — 4pf Trimmer Osc.		C18	0.1 uf 100 vw Hi-K Disc	227038
C5	0.01 uf 200 vw Hunts W99	228609	C19	75 uf 10 vw Electrolytic	229675
C6	0.005 uf 200 vw Hunts W 99	226005	C20	10 uf 3 vw Electrolytic	228757
C7	330 pf ± 5% 600 vw Styroseal	223712	C21	25 uf 3 vw Electrolytic	229562
C8	0.01 uf 200 vw Hunts W99	228609	C22	5 uf 6 vw Electrolytic	228253
C9	4.7 pf ± 5% NPO Tubular	220219	C23	0.01 uf 200 vw Hunts W99	228609
C10	0.01 uf 200 vw Hunts W99	228609	C24	25 uf 3 vw Electrolytic	229562
C11	25 uf 3 vw Electrolytic	229562	C25	0.01 uf 200 vw Hunts W99	228609
C12	330 pf ± 5% 600 vw Styroseal	223712	C26	0.04 uf 200 vw Hunts W99	228750
C13	0.01 uf 200 vw Hunts W99	228609	C27	0.04 uf 200 vw Hunts W99	228750
C14	4.7 pf ± 5% NPO Tubular	220219	C28	0.1 uf 100 vw Hi-K Disc	227038

TRANSFORMERS

Code No.	Description	Part No.	Code No.	Description	Part No.
T1	Ferrite Rod Aerial	38755	T5	2nd I.F. Transformer	38749
T2	Oscillator Coil	38753	T6	Driver Transformer	38155
T3	Converter I.F. Transformer	38751	T7	Output Transformer	38158
T4	1st I.F. Transformer	38747			

TRANSISTORS

Code No.	Description	Part No.	Code No.	Description	Part No.
VT1	2N412		VT6	2N408	
VT2	2N410		VT7	2N408	
VT3	2N410		MR1	Germanium Diode GEX 34	
VT4	2N406		MR2	Germanium Diode GEX 34	
VT5	2N408		MR3	Germanium Diode GEX 34	

MISCELLANEOUS

Code No.	Description	Part No.	Code No.	Description	Part No.
TH1	130 ohms at 25 degrees C. N.T.C.	893703	LS1	2¾-inch Permanent Magnet Speaker	50000
SW1	On/Off Switch (on R14).				