



TRANSISTOR TEST POINTS FOR MODELS

NA91 NA92 NA93 NA94

All Readings read from Negative line at full volume off station APPROX. Readings at 14 Volts.

AC188	AC187	AC125	BC148	0A90	BF195	BF194	BF194
C8 0	C7 14	C6 7.9	C5 13.6	.15	C4 11.4	C3 11.4	C2 11.4
B8 7.7	B7 7.9	B6 13.6	B5 10.5	B4 2	B3 1.4	B2 2.1	B1 1.4
E8 7.8	E7 7.8	E6 13.8	E5 11.3	E4 1.3	E3 .8	E2 1.5	E1 .8

The Standing current in the output transistors must be finally adjusted when set is warm at point (*) (Collector of AC188) to 8MA at 14 Volts.